



Westinghouse

INNOVATION YOU CAN BE SURE OF

Consumer Guide

Inverter Generator Comparison

| |  |  |  |
|---------------------------------------|---|--|---|
| | Westinghouse iGen1200 | Honda EU10i | Yamaha EF1000iS |
| Engine Displacement | 54 cc | 49 cc | 50 cc |
| Rated Electrical Output | 1,000 W (1.0 kVA) | 900 W (0.9 kVA) | 900 W (0.9 kVA) |
| Maximum Electrical Output | 1,200 W (1.2 kVA) | 1,000 W (1.0 kVA) | 1,000 W (1.0 kVA) |
| Rated AC Electrical Voltage | 240 Volts | 240 Volts | 230 Volts |
| 240 Volt AC Socket Outlets | 1 | 1 | 1 |
| 240 Volt AC Overload Reset | Engine Restart | Engine Restart | Engine Restart |
| 12 Volt DC Cig. Lighter Socket | Yes | No | No |
| USB Fast Charger Socket | Yes | No | No |
| Digital Hour Meter | Yes | No | No |
| Single-Sided Control Access | No | No | Yes |
| Dimensions L x W x H | 46 x 26 x 40 cm | 45 x 24 x 38 cm | 45 x 24 x 38 cm |
| Weight (Dry) | 15 kg | 13 kg | 12.7 kg |
| Fuel Tank Capacity | 2.8 Litres | 2.1 Litres | 2.5 Litres |
| Fuel Level Gauge | No | No | No |
| Fuel Shutoff Valve | Yes | Yes | Yes |
| Run Time @ 225 Watts | 9 Hours | 8 Hours | 12 Hours |
| Run Time @ 900 Watts | 4.5 Hours | 4 Hours | Not Stated |
| Noise Level @ 225 Watts (7 m) | 52 dB(A) | 52 dB(A) | 47 dB(A) |
| Noise Level @ 900 Watts (7 m) | 58 dB(A) | 58 dB(A) | 57 dB(A) |
| Warranty (Personal Use) * | 2 Years | 4 Years ^Δ | 4 Years |
| Warranty (Commercial Use) * | 1 Year | 1 Year | 1 Year |
| Recommended Retail Price | \$899 | \$1,499 | \$1,549 |

Source: Manufacturers' websites as at 11 April 2020.

* Conditions apply.

Δ To qualify, the generator must be serviced for the entire warranty period by an authorised Honda dealer.

2020-04-11

Power - when you need it - where you need it

westinghouseoutdoorpower.com.au