



Westinghouse

INNOVATION YOU CAN BE SURE OF

Consumer Guide

Inverter Generator Comparison

	 Westinghouse iGen4500s	 Honda EU30is	 Yamaha EF3000iSE
Engine Displacement	224 cc	196 cc	171 cc
Electric Start with Remote Control	Yes	No	No
Auto Choke	Yes	No	No
Rated Electrical Output	3,700 W (3.7 kVA)	2,800 W (2.8 kVA)	2,800 W (2.8 kVA)
Maximum Electrical Output	4,500 W (4.5 kVA)	3,000 W (3.0 kVA)	3,000 W (3.0 kVA)
Rated AC Electrical Voltage	240 Volts	240 Volts	230 Volts
240 Volt AC Socket Outlets	2	2	2
240 Volt AC Overload Reset	Push Button	Engine Restart	Engine Restart
12 Volt DC Cig. Lighter Socket	Yes	No	No
USB Fast Charger Socket	Yes	No	No
Digital Multifunction Display	Yes	No	No
Wheels	Yes	No	Yes
Dimensions L x W x H	65 x 48 x 52 cm	66 x 45 x 56 cm	68 x 45 x 56 cm
Weight (Dry)	49.5 kg	59 kg	67 kg
Fuel Tank Capacity	13.5 Litres	13 Litres	13 Litres
Fuel Level Gauge	Yes	Yes	Yes
Fuel Shutoff Valve (Independent)	Yes	Yes	Yes
Run Time @ 700 Watts	19 Hours	20 Hours	20.5 Hours
Run Time @ 2,800 Watts	7.5 Hours	7.1 Hours	Not Stated
Noise Level @ 700 Watts (7 m)	52 dB(A)	52 dB(A)	51 dB(A)
Noise Level @ 2,800 Watts (7 m)	62 dB(A)	65 dB(A)	57 dB(A)
Warranty (Personal Use) *	2 Years	4 Years ^Δ	4 Years
Warranty (Commercial Use) *	1 Year	1 Year	1 Year
Recommended Retail Price	\$2,499	\$4,239	\$4,929

Source: Manufacturers' websites as at 11 April 2020.

* Conditions apply.

Δ To qualify, the generator must be serviced for the entire warranty period by an authorised Honda dealer.

2020-04-11

Power - when you need it - where you need it

westinghouseoutdoorpower.com.au